



# CINT2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

Fujitsu Limited  
PRIMEPOWER850 (1350MHz)

SPECint\_rate2000 = 154  
SPECint\_rate\_base2000 = 132

SPEC license #: 19 | Tested by: Fujitsu Limited | Test date: Jun-2003 | Hardware Avail: Aug-2003 | Software Avail: May-2003

| Benchmark   | Base Copies | Base Runtime | Base Ratio | Copies | Runtime | Ratio |
|-------------|-------------|--------------|------------|--------|---------|-------|
| 164.gzip    | 16          | 229          | 113        | 16     | 205     | 127   |
| 175.vpr     | 16          | 227          | 114        | 16     | 211     | 123   |
| 176.gcc     | 16          | 196          | 104        | 16     | 131     | 156   |
| 181.mcf     | 16          | 375          | 89.0       | 16     | 278     | 120   |
| 186.crafty  | 16          | 118          | 158        | 16     | 114     | 163   |
| 197.parser  | 16          | 276          | 121        | 16     | 253     | 132   |
| 252.eon     | 16          | 227          | 106        | 16     | 148     | 163   |
| 253.perlbnk | 16          | 211          | 158        | 16     | 209     | 160   |
| 254.gap     | 16          | 170          | 120        | 16     | 159     | 128   |
| 255.vortex  | 16          | 149          | 237        | 16     | 119     | 296   |
| 256.bzip2   | 16          | 202          | 138        | 16     | 193     | 145   |
| 300.twolf   | 16          | 305          | 182        | 16     | 291     | 191   |

### Hardware

CPU: SPARC64 V  
 CPU MHz: 1350  
 FPU: Integrated  
 CPU(s) enabled: 16 cores, 16 chips, 1 core/chip  
 CPU(s) orderable: 1 to 16 (increments of 1)  
 Parallel: None  
 Primary Cache: 128KBI+128KBD on chip  
 Secondary Cache: 2MB(I+D) on chip  
 L3 Cache: None  
 Other Cache: None  
 Memory: 65536MB  
 Disk Subsystem: 1 x 36.4GB SCSI (10000rpm)  
 Other Hardware: None

### Software

Operating System: Solaris8 2/02 with current patches (see notes)  
 Compiler: Fujitsu Parallelnavi 1.0.2  
 Sun ONE Studio 8  
 Sun Performance Library 8  
 File System: ufs  
 System State: multi user

## Notes/Tuning Information

Baseline (except 252.eon, for Sun ONE Studio 8):

```
-fast -xtarget=ultra3cu -xipo=2 ONESTEP=yes
fdo_pre0=rm -rf ./feedback.profile ./SunWS_cache
PASS1=-xprofile=collect:./feedback
PASS2=-xprofile=use:./feedback
```

Baseline (252.eon, for Sun ONE Studio 8):

```
-fast -xchip=ultra3cu -xarch=v8plusb -xipo=2 ONESTEP=yes
```

Peak

(for Sun ONE Studio 8)

```
fdo_pre0=rm -rf ./feedback.profile ./SunWS_cache
PASS1=-xprofile=collect:./feedback
PASS2=-xprofile=use:./feedback
```

```
164.gzip: -x05 -xchip=ultra2 -xcache=128/64/2:2048/64/4 -xarch=v8plusb
-xalias_level=std -xipo=2 -xprefetch
-W2,-whole,-Ainline ONESTEP=yes
```

```
175.vpr: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
-xchip=ultra2 -xalias_level=std -xipo=2 -xsfpcnst -xdepend -W2,-whole
-Wc,-Qeps:enabled=1,-Qeps:do_spec_load=1,-Qeps:rp_filtering_margin=100
-lmopt -lm ONESTEP=yes
```



# CINT2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

Fujitsu Limited  
PRIMEPOWER850 (1350MHz)

SPECint\_rate2000 = 154  
SPECint\_rate\_base2000 = 132

SPEC license #: 19 | Tested by: Fujitsu Limited | Test date: Jun-2003 | Hardware Avail: Aug-2003 | Software Avail: May-2003

## Notes/Tuning Information (Continued)

```

176.gcc: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra3 -xipo=2 -xprefetch=latx:2.0 -W2,whole
        -Wc,-Qgsched-trace_late=1,-Qgsched-T4 -l12amm ONESTEP=yes
181.mcf: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra2 -xipo=2 -xdepend -Wc,-Qms_pipe-pref,-Qeps:enabled=1
        -xprefetch_level=3 -W2,-Apf:l1list=3:notinl1list -lprism32 ONESTEP=yes
186.crafty: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xipo=2 -xalias_level=strong
        -W2,-Ashort_ldst ONESTEP=yes
197.parser: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xipo=2 -xalias_level=strong -xdepend -xregs=syst
        -Wc,-Qgsched-trace_late=1,-Qgsched-T6,-Qipa:valueprediction -lprism32 ONESTEP=yes
252.eon: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra3 -xipo=2 -xregs=syst -xalias_level=compatible -noex -xunroll=3
        -xprefetch=latx:0.8 -Qoption iropt -Mt2000
        -Qoption cg -Qgsched-trace_late=1,-Qgsched-T4,-Qeps:enabled=1,-Qeps:ws=32
        -lmopt ONESTEP=yes
253.perlbnk: -dn -x05 -xchip=ultra3 -xcache=128/64/2:2048/64/4
        -xarch=v8plus -xipo=2 ONESTEP=yes
254.gap: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra3 -xipo=2 -xalias_level=strong -xvector -xprefetch_level=3
        -W2,-whole,-Abcopy -Wc,-Qgsched-trace_late=1,-Qgsched-T4 ONESTEP=yes
255.vortex: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra2 -xrestrict -xipo=2 -xdepend -xprefetch=latx:2.4
        -W2,-crit,-Ainline:recursion=1:cs=500:irs=6000,-Aheap,-reroll=1,-Aunroll,-Ms15,-Mt300,-Mr6000
        -Wc,-Qeps:enabled=1,-Qeps:do_spec_load=1,-Qdepgraph-early_cross_call=1
        -Wc,-Qiselect-funcalign=32,-Qpeep-Sh0 -l12amm -lprism32 ONESTEP=yes
256.bzip2: -fast -xarch=v8plusb -xchip=ultra3cu -xcache=128/64/2:2048/64/4
        -xchip=ultra3 -xipo -xalias_level=strong -xdepend -xregs=syst
        -xrestrict -xprefetch=latx:1.6 -W2,-Abopt
        -Wc,-Qiselect-funcalign=64,-Qeps:enabled ONESTEP=yes

```

(for Parallelnavi 1.0.2)

```

300.twolf: -Kfast_GP=5,GREG,popt,cfunc,staticclump,use_rodatta,
        xi=10,nounroll,largepage,bcopy,prefetch=4 -dy
        PASS1=-Kpg PASS2=-Kpu=$(EXEBASE).fbk
        ONESTEP=yes

```

Portability:

```

176.gcc: -Dalloca=__builtin_alloca -DHOST_WORDS_BIG_ENDIAN
186.crafty: -DSUN
252.eon: -library=iostream
253.perlbnk: -DSPEC_CPU2000_SOLARIS
254.gap: -DSYS_IS_USG -DSYS_HAS_TIME_PROTO -DSYS_HAS_SIGNAL_PROTO
        -DSYS_HAS_CALLOC_PROTO -DSYS_HAS_IOCTL_PROTO

```

Note:

```

System Tunables: (for /etc/system)
set consistent_coloring=1,
set shmsys:shminfo_shmmax=8589934592,set shmsys:shminfo_shmmni=256,
set shmsys:shminfo_shmseg=400,set shmsys:shminfo_shmmmin=1
set tune_t_fsflushr = 86400
set autoup = 86400

```

```

System Tunables: (for /etc/opt/FJSVpnm/lpg.conf)
TSS=4096M, SHMSEGSIZE=256M

```

Shell Environments:



# CINT2000 Result

Copyright ©1999-2004, Standard Performance Evaluation Corporation

Fujitsu Limited  
PRIMEPOWER850 (1350MHz)

SPECint\_rate2000 = 154  
SPECint\_rate\_base2000 = 132

SPEC license #: 19 | Tested by: Fujitsu Limited | Test date: Jun-2003 | Hardware Avail: Aug-2003 | Software Avail: May-2003

## Notes/Tuning Information (Continued)

```
LD_LIBRARY_PATH="/opt3/SUNWspro/prod/lib/v8plusb"  
PRISM_HEAP=268435456  
PRISM_MODE=2
```

ONESTEP=yes was set for all baseline and peak benchmarks.  
Feedback directed optimization was used for all baseline and peak benchmarks except 252.eon(base).

Processes were bound to CPUs using "submit=pbind".

Stack size set to unlimited via "ulimit -s unlimited".

Sun ONE Studio 8, posted at URL <http://www.sun.com/software/sundev/suncc/> was used for this submission.

All patches for Solaris8 posted at

[http://access1.sun.com/patch.public/cgi-bin/show\\_list.cgi/wrk/Sun\\_ONE\\_Studio\\_7\\_SPARC\\_SunOS\\_5.8](http://access1.sun.com/patch.public/cgi-bin/show_list.cgi/wrk/Sun_ONE_Studio_7_SPARC_SunOS_5.8) as of date 2003/04/21 were applied: 108434-12, 108435-12, 111697-04, 111721-03.